

VESTA-409

ADC-IR-32-SL



VESTA Radio PIR Detector



- PIR detector via radio VESTA
- Coverage of 12 meters, 90°
- Specially manufactured lens to reduce dead angle
- Two selectable sensitivity levels
- Anti-pet 25 kg
- Flexible installation height from 2.3 to 2.5 meters
- Powered by 1 CR123 battery
- Battery life of 7.6 years.



| Reference / Model | VESTA-409 / ADC-IR-32-SL |
|--|--------------------------|
| New generation microprocessor-controlled PIR detector VESTA | |
| Designed to avoid false alarms triggered by pets or small and medium-sized animals (up to 25 kg) | |
| Special lens with advanced technology to help reduce blind spots | |
| Detection range: 12 meters, 90°. | |
| Two selectable sensitivity levels | |
| RF frequency: 868MHz | |
| High false alarm immunity | |
| Tamper protection against tampering | |
| Automatic power saving mechanism | |
| Random supervisory signals for system integrity | |
| Rejection of radio interference | |
| Powered by 1 CR123 battery | |
| Battery life of 7.6 years | |

VESTA-409

ADC-IR-32-SL



VESTA Radio PIR Detector

| Reference / Model | VESTA-409 / ADC-IR-32-SL |
|--|--------------------------|
| Operating temperature -10°C ~ +45°C (-10°C ~ +45°C) | |
| Relative humidity up to 85% (non-condensing) | |
| Installation height of 2.3 ~ 2.5 meters (8 ~ 8.5 feet) | |
| Dimensions: 72 (W) x 98 (H) x 46 mm | |