

Radio curtain PIR detector





- Radio curtain PIR detector
- Coverage up to 10 meters, 10 ° x110 °
- It can be installed on the ceiling
- Tamper proof
- Powered by 1 3V CR123A lithium battery
- 5 year battery life



Reference / Model	VESTA-051 / IRC-29-F1
Features	
Microprocessor controlled with ADSP algorithms	
Wall or ceiling mount with tamper protection	
Random monitoring that verifies system integrity	
Sensitivity control with temperature compensation	
Battery operated for easy installation	
LED works as a fault indicator and test mode	
White light and noise rejection	
Detection range up to 10 meters	
Automatic energy saving mechanism	
Meets CE requirements	
Compact and low-profile with insect resistance	
Fpecs	



Radio curtain PIR detector

Reference / Model	VESTA-051 / IRC-29-F1
RF frequency: 868MHz	
Power: 1 3V CR123A lithium battery	
5 year battery life	
Detection range: 10 meters, 110 ° x10 °	
Installation height: 1.4 ~ 1.6 meters	
-10 ° C ~ + 45 ° C operating temperature	
Relative humidity up to 85% (without condensation)	
Dimensions: 56 (W) x 76 (H) x 43mm	