

BX-32-BUS Outdoor Bell Box

Hardwired Bell Box with Effective System Alert Indication



- BUS Connection to Hybrid Panel
- BUS Connection to Multiple Devices
- Siren output level is 104dB at 1 meter

Powered by Hybrid Panel through BUS connection, BX-32-BUS is an outdoor siren designed to be fitted in the front of the property in a highly visible position, working with Hybrid Panel to provide a permanent visual deterrent to intruders. It is also capable of BUS connection of several devices at once for enhanced flexibility and redundancy.

When alarm signal is received from Control Panel, BX-32-BUS will activate its siren and strobe light to attract attention. BX-32-BUS can also work with the Control Panel to emit entry, exit delay, low battery beeps and also alert you to tamper violation. It is easy to install and energy efficient.

BX-32-BUS's tamper-deterrent feature protects against unauthorized removal and sabotage. Encased in an elegant, weather resistant IPX5 waterproof design, BX-32-BUS is a premium choice for the modern smart home.

Features

- Siren output level is 104dB at 1 meter
- Unique alarm sounds for fire and burglary
- Four Selectable Siren Volume Levels
- Programmable siren duration of 3/5/10 minutes
- Beep notifications of arming/disarming, door chime, and low battery status
- IPX5 waterproof and UV resistant housing
- IPX5 waterproof and UV resistant housing
- Lightweight and flexible to install
- Smaller, visually pleasing design
- Cover tamper protection prevents unauthorized removal and sabotage
- Low battery detection
- EN Compliance

Specifications

BX-32-BUS

Power Source	From BUS connection to the control panel: BUS 13.5V DC
Current Consumption (In Standby Mode)	0.88 mAh
Current Consumption (Maximal)	54.8 mAh
Siren Output	104dB at 1 meter
Operating Temperature	-25°C to 60°C (-13°F to 140°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	180mm x 57.7mm x 213.6mm

* Note: Actual battery life may vary with product settings, operating environment and usage.