

VESTA-042

PSM-29-ZW



VESTA switch / power meter



- VESTA switch / power meter
- Allows remote devices to be activated / deactivated through the web or app
- Allows scenes for automation
- It incorporates a power and consumption meter
- Compatible with third-party Z-Wave devices



Reference / Model	VESTA-042 / PSM-29-ZW
Features	
Allows user to remotely turn on / off connected devices	
Built-in power meter to measure and generate an energy history during the day / week / month	
Allows home automation and security systems to turn appliances on / off according to custom schedules and scenes	
Ability to duplicate as a Z-Wave repeater	
Charging type: electronic gadgets	
Over-the-air firmware update (OTA) capability	
Can be controlled remotely or manually	
Compatible with third-party Z-Wave systems	
System status indicator LED	
CE compliance	
specs	

VESTA-042

PSM-29-ZW



VESTA switch / power meter

Reference / Model	VESTA-042 / PSM-29-ZW
	RF frequency. 868.40MHz
	Communication protocol: Z-Wave Plus 500 module
	Power: 110V ~ 230V AC, 50 / 60Hz
	Maximum load: 1760W, 16A, 110V AC / 3680W 16A, 230V AC
	-10 ° C ~ + 45 ° C operating temperature
	Relative humidity up to 85% (without condensation)
	Dimensions: 52 (W) x 78 (H) x 85.8mm