

QallMax 160-zone radio touch panel



- Gateway VESTA QallMax home security system with 7" touch screen
- 160 zones via radio
- 80 users, 8 partitions
- 5MP front camera for face detection
- Supports RF 868-F1 (up to 2 km) and Z-Wave devices
- Compatible with PIRCAMS HD SF1 protocol
- TCP/IP, WiFi and 4G LTE connectivity
- Bluetooth for contactless disarming
- Bidirectional voice communication
- Domotics and live monitoring
- iOS and Android App and web browser
- EN50131 Grade 2 certified.



Reference / Model	VESTA-425 / QALLMAX TOUCHPANEL-3
160 radio zones	
80 users	
8 partitions	
7" LCD touch screen (1024x600)	
5MP front camera for face detection	
TCP/IP, WiFi (2.4/5GHz) and LTE communications	
Built-in 4G module	
Bluetooth 5.0 for contactless disarming	
MicroSD card slot (not included)	
Supports RF 868-F1 and Z-Wave devices	
Compatible with HD transmission devices (PIRCAMS) with SF1 protocol	
Live visual verification	
Home automation	
Energy management	
24/7 emergency monitoring	

QallMax 160-zone radio touch panel

Reference / Model	VESTA-425 / QALLMAX TOUCHPANEL-3
Remote management	
Built-in 95dB siren	
Z-Wave Protocol: Z-Wave Plus 800	
RF Frequency: 868MHz	
Power supply: 5V DC, 3A, Type C	
3.7V /2500 mAh lithium polymer backup battery	
Operating Temperature -10°C ~ +45°C	
Relative humidity: Up to 85% (non-condensing)	
Dimensions: 192 (W) x 153 (H) x 31 mm	
EN50131 Grade 2 certified	